
#### **FEATURES**

- Low Dropout Voltage 500mV at 1.5A Output Current
- Fast Transient Response
- 0.015% Line Regulation
- 0.1% Load Regulation
- Internal Thermal and Current Limiting
- Adjustable or Fixed Output Voltage(1.5, 2.5, 2.85, 3.0, 3.3, 5.0V)
- Surface Mount Package SOT-223 & TO-263 (D2 Package)
- 100% Thermal Limit Burn-in

### **APPLICATIONS**

- Battery Charger
- Adjustable Power Supplies
- Constant Current Regulators
- Portable Instrumentation
- High Efficiency Linear Power Supplies
- High Efficiency "Green" Computer Systems
- SMPS Post-Regulator
- Power PC Supplies
- Powering VGA & Sound Card



ORDERING INFORMATION				
Device Name	Package			
LM1086S-XX	SOT 223			
LM1086RS-XX	TO252(D)			


(XX=Vout=1.5V, 2.5V, 2.85V, 3.0V, 3.3V, 5.0V Adjustable= AD)

#### DESCRIPTION

The LM1086 is a low dropout three terminal regulators with 1.5A output current capability. The output voltage is adjustable with the use of a resistor divider. Dropout is guaranteed at a maximum of 500 mV at maximum output current.

It's low dropout voltage and fast transient response make it ideal for low voltage microprocessor applications. Internal current and thermal limiting provides protection against any overload condition that would create excessive junction temperature.

## **TEST & TYPICAL APPLICATION CIRCUIT**



# 1.5A L.D.O. VOLTAGE REGULATOR (Adjustable & Fixed)

# ABSOULTE MAXIMUM RATINS

CHARACTERISTIC	SYMBOL	VALUE	UNIT
Supply Voltage	Vin	7	V
Operating Junction Temperature Range	Topr	0~125	$^{\circ}$
Storage Temperature Range	Tstg	-65~150	$^{\circ}$
Thermal Resistance Junction to Case TO-263	Tjc	3	C/W
Thermal Resistance Junction to Ambient TO-263	Tja	60	C/W
Lead Temperature (Soldering) 10 sec.	Tsol	300	$^{\circ}$
Maximum Output Current	Imax	1.5	А

# ELECTRICAL CHARACTERISTICS I $_{OUT}$ =100mA, $T_{A}$ =25 $^{\circ}$ C, unless otherwise specified

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT			
1.5V Version								
Output Voltage	0 <i<sub>OUT&lt;1.5A, 2.75V<v<sub>IN&lt;7V</v<sub></i<sub>	1.485	1.5	1.515	V			
2.5V Version								
Output Voltage	0 <i<sub>OUT&lt;1.5A, 3.5V<v<sub>IN&lt;7V</v<sub></i<sub>	2.475	2.5	2.525	V			
2.85V Version								
Output Voltage	0 <i<sub>OUT&lt;1.5A, 4.35V<v<sub>IN&lt;7V</v<sub></i<sub>	2.822	2.85	2.879	V			
3.0V Version								
Output Voltage	0 <i<sub>OUT&lt;1.5A, 4.5V<v<sub>IN&lt;7V</v<sub></i<sub>	2.97	3	3.03	V			
3.3V Version		<u> </u>						
Output Voltage	0 <i<sub>OUT&lt;1.5A, 4.75V<v<sub>IN&lt;7V</v<sub></i<sub>	3.27	3.3	3.33	V			
5.0V Version	1	Į.						
Output Voltage	0≤I <sub>OUT</sub> ≤1.5A, 5.5V≤V <sub>IN</sub> <7V	4.95	5	5.05	V			
All Voltage Options	-	I						
Reference Voltage (V <sub>REF</sub> )	$V_{IN} \le 7V, P \le P_{MAX}$ 1.5 $V \le (V_{IN} V_{OUT}) \le 5.75V, 10 \text{ mA} \le I_{OUT} \le 1.5A$	1.225 1.225	1.25 1.25	1.27 1.27	V			
Min. Load Current(Note 3)	1.5V≤(V <sub>IN</sub> -V <sub>OUT</sub> )≤5.75V		5	10	mA			
Line Regulation (ΔV <sub>REF</sub> (V <sub>IN</sub> ))	2.75V≤V <sub>IN</sub> ≤7V, I <sub>OUT</sub> =10mA, T <sub>J</sub> =25℃		0.005	0.2	%			
Load Regulation (ΔV <sub>REF</sub> (V <sub>OUT</sub> ))	10mA≤I <sub>OUT</sub> ≤1.5A,(V <sub>IN</sub> -V <sub>OUT</sub> )=3V,T <sub>J</sub> =25°C		0.05	0.3	%			
Dropout Voltage	$\Delta V_{REF}$ =1% , lout=1.5A		1.1	1.2	V			
Current Limit I <sub>OUT</sub> (MAX)	Vin-Vout=3V 1.4V≤(V <sub>IN</sub> -V <sub>OUT</sub> ) Adjustable Only	1.7	2.5		А			
Long Term Stability	T <sub>A</sub> =125℃, 1000Hrs		0.3	1	%			
Thermal Regulation (ΔV <sub>OUT</sub> (Pwr))	T <sub>A</sub> =25℃, 30ms pulse		0.01	0.02	%/W			
Output Noise, RMS	10Hz to 10Khz T <sub>A</sub> =25℃	0.003			%/Vo			
Thermal Resistance	Junction to Tab			3	°C/W			
	Junction to Ambient			60				